



DC Battery Pack



Features:

- **Converts AC Electromagnetic Yoke into DC**
- **Portable DC Power Supply**
- **Constant Battery Voltage Monitoring**
- **Visual and Audible Warning and Alarms**
- **100% portable for field use.**
- **Standard and Extended version**
- **Multi-Compartment Carry Bag**



4a Cartwright Street
CE6
Vanderbijlpark
Gauteng
South Africa

Phone: +27 16 931 3068
Fax: 086 508 2374
E-mail: johannv@industronic.co.za



Technical Data

Description	Clarification	Condition
Battery Type		12Volt 3Ah Sealed Lead Acid (Standard) or 12 Volt Sealed Lead Acid (Extended)
Battery Run Time	Standard	7Hrs Continuous
	Extended	3Hrs Continuous
Battery Indication (Variable Colour LED)	Green	13.8 Volts - 12.5 Volts
	Amber	12.0 Volts - 11.5 Volts
	Red	11.0 Volts - 10.5 Volts
	Flashing Red	< 10.5 Volts with Audible alarm at short intervals
Cut-off level	Red	< 10.0 Volts with continuous Audible Alarm
12 Volt Intelligent Battery Charger	Input Voltage	AC 95V - 260V
	Output Voltage	DC 12V
	Current	7A
Weight	Standard	4Kg
	Extended	6Kg